

Datamate L-Tek Connectors

Female Crimp Kit

- Part numbers are for a complete kit of a housing and the applicable number of contacts.
- Contacts are rear insertable.
- Spare contacts are available – see the following page.



SINGLE ROW	CALCULATION	DOUBLE ROW	CALCULATION
	A B + 5.15		A B + 5.15
	B (Total no. of contacts - 1) x 2		B Total no. of contacts - 2

TOOLS	WIRE STRIPPING DETAILS
<p>Recommended Crimp Tool - M22520/2-01</p> <p>Positioner - T5747</p> <p>Contact Insertion/Removal Tool - Z80-280</p> <ul style="list-style-type: none"> Spare and pre-cabled contacts shown on following pages. Instruction sheets available at www.harwin.com/instructions. 	

HOW TO ORDER

M80 - XXX XX XX

SERIES CODE

TYPE	
798	Single Row, Extra Small Bore (28-32 AWG)
898	Single Row, Small Bore (24-28 AWG)
899	Single Row, Large Bore (22 AWG)
788	Double Row, Extra Small Bore (28-32 AWG)
888	Double Row, Small Bore (24-28 AWG)
889	Double Row, Large Bore (22 AWG)

FINISH

01	Gold + Tin
05	Gold

TOTAL NO. OF CONTACTS

02 to 07, 17	Single Row
04, 06, 08, 10, 12, 14, 16, 18, 20, 26, 34	Double Row

All dimensions in mm.