



Triad Magnetics

460 Harley Knox Blvd

Perris CA 92571



Tel: 951.277.0757 • Fax: 951.277.2757

Email: info@triadmagnetics.com • Website:

www.triadmagnetics.com

Item # FIT80-6, Switch Mode/High Frequency Differential Mode Toroidal Inductors

Triad toroidal inductors are specifically designed to minimize transients. These devices store energy, and therefore, condition the output signal by leveling out the current waveform providing a more stable current supply. Generally used in high frequency circuits, our standardized design provides an economical solution in differential mode applications or as an output inductor.



[Check Stock](#) | [Specifications](#) | [Technical Notes](#) | [Note](#)

Check Stock

Click here to check stock >>

CHECK STOCK ✓

Specifications

Min. Inductance (No Bias)	38.70 μ H
Min. Inductance at Bias	18.11 μ H
DC Current Rating	9.7 A

Max. DCR	17 Ohm 17.0 mOhm
Dimension (A)	0.975 in
Dimension (B)	0.625 in
Dimension (C)	1.100 in
Dimension (D)	0.450 in
Dimension (E)	0.045 in
Weight	0.045 lb

Technical Notes

1. Nominal inductance values are typically 10 % higher than minimal rating.
2. Biased inductance measured at rated DC amps.
3. Operation at rated current yields approximately 40°C temperature rise over 20 °C ambient.

Note

A FIT-KIT is available which includes one of each of the above listed components.